

FURUNO

INSTALLATION MANUAL

MODEL 1824C-BB MARINE RADAR
MODEL 1834C-BB MARINE RADAR
MODEL 1934C-BB MARINE RADAR
MODEL 1944C-BB MARINE RADAR
MODEL 1954C-BB MARINE RADAR
GD-1920C-BB COLOR VIDEO PLOTTER



FURUNO ELECTRIC CO., LTD.
NISHINOMIYA, JAPAN



(Elemental Chlorine Free)

The paper used in this manual
is elemental chlorine free.

© **FURUNO ELECTRIC CO., LTD.**

9-52 Ashihara-cho,
Nishinomiya 662-8580, JAPAN

Telephone : 0798-65-2111

Fax : 0798-65-4200

Your Local Agent/Dealer

All rights reserved.

Printed in Japan


FIRST EDITION : FEB. 2005

Pub. No. IME-35490-A

(DAMI) M1804C-BB_GD1920C-BB



00015180600



IME35490A00



SAFETY INSTRUCTIONS



WARNING



Do not open the equipment unless totally familiar with electrical circuits and service manual.

**ELECTRICAL
SHOCK
HAZARD**

Only qualified personnel should work inside the equipment.



Wear a safety belt and hard hat when working on the antenna unit.

Serious injury or death can result if someone falls from the radar mast.

Construct a suitable service platform from which to install the antenna unit.

Serious injury or death can result if someone falls from the radar mast.

Turn off the power at the mains switch-board before beginning the installation.

Fire, electrical shock or serious injury can result if the power is left on or is applied while the equipment is being installed.



CAUTION

Observe the following compass safe distances to prevent deviation of a magnetic compass.

	Standard	Steering
Processor unit	1.40 m	0.90 m
Control unit	0.45 m	0.30 m
MODEL1824C-BB antenna unit	1.25 m	0.85 m
MODEL1834C-BB antenna unit	0.90 m	0.70 m
MODEL1934C-BB antenna unit	1.00 m	0.80 m
MODEL1944C-BB antenna unit	1.00 m	0.80 m
MODEL1954C-BB antenna unit	1.00 m	0.75 m
Power supply unit (1954C-BB)	1.40 m	0.95 m



WARNING

Radio Frequency Radiation Hazard

The radar antenna emits electromagnetic radio frequency (RF) energy which can be harmful, particularly to your eyes. Never look directly into the antenna aperture from a close distance while the radar is in operation or expose yourself to the transmitting antenna at a close distance.

Distances at which RF radiation levels of 100 and 10 W/m² exist are given in the table below.

Note: If the antenna unit is installed at a close distance in front of the wheel house, your administration may require halt of transmission within a certain sector of antenna revolution. This is possible - Ask your FURUNO representative or dealer to provide this feature.

MODEL	Distance to 100 W/m ² point	Distance to 10 W/m ² point
MODEL 1824C-BB	Nil	Worst case 0.50 m
MODEL 1834C-BB	Nil	Worst case 1.80 m
MODEL 1934C-BB	Worst case 0.20 m	Worst case 3.00 m
MODEL 1944C-BB	Nil	Worst case 2.50 m
MODEL 1954C-BB	XN12A	Worst case 2.50 m
	XN13A	Worst case 2.30 m

TABLE OF CONTENTS

EQUIPMENT LISTS	iii
SYSTEM CONFIGURATIONS	v
1. MOUNTING	1-1
1.1 Mounting the Control Unit.....	1-1
1.2 Mounting the Processor Unit	1-4
1.3 Mounting the Antenna Unit of MODEL1824C-BB	1-5
1.4 Mounting the Antenna Unit of MODEL1834C-BB	1-13
1.5 Mounting the Antenna Unit of MODEL1934C-BB/1944C-BB/1954C-BB	1-18
1.6 Mounting the Power Supply Unit for MODEL1954C-BB	1-27
2. WIRING.....	2-1
2.1 Standard Wiring.....	2-1
2.2 Wiring the Power Supply Unit for MODEL 1954C-BB	2-4
3. SETTING UP THE EQUIPMENT	3-1
3.1 Setting up with the Installation Wizard.....	3-1
3.2 Checking Magnetron Heater Voltage	3-13
4. OPTIONAL EQUIPMENT	4-1
4.1 External Buzzer	4-1
4.2 ARP Kit ARP-11.....	4-2
PACKING LISTS	A-1
OUTLINE DRAWINGS	D-1
INTERCONNECTION DIAGRAMS	S-1

EQUIPMENT LISTS

Standard supply

Name	Type	Code No.	Qty	Remarks	
Control unit	RCU-017	-	1		
Processor unit	RPU-015	-	1		
Antenna unit	RSB-0094-0075	-	1	MODEL1824C-BB	
	RSB-0071-057	-		MODEL1834C-BB	
	XN10A-RSB-0070-064	-		MODEL1934C-BB, 24 rpm	
	XN10A-RSB-0073-064	-		MODEL1934C-BB, 48 rpm	
	XN12A-RSB-0070-059	-		MODEL1944C-BB, 24 rpm	
	XN12A-RSB-0073-059	-		MODEL1944C-BB, 48 rpm	
	XN12A-RSB-0072-060	-		MODEL1954C-BB, 4ft, 24 rpm	
	XN12A-RSB-0073-060	-		MODEL1954C-BB, 4ft, 48 rpm	
	XN13A-RSB-0072-060	-		MODEL1954C-BB, 6ft, 24 rpm	
Power supply unit	PSU-005	-	1	For MODEL 1954C-BB	
Installation materials	CP03-26000	000-080-049	1set	MJ-A7SPF0006-050	For control unit
	CP03-26100	000-080-536		MJ-A7SPF0006-100	
	CP03-25900	000-080-542	1	For Processor unit: MJ-A3SPF0018-050Z, CP03-25901	
	CP03-21800	000-080-014	1	For MODEL1824C-BB/1834C-BB 10 m signal cable	
	CP03-21810	000-080-015		For MODEL1824C-BB/1834C-BB 15 m signal cable	
	CP03-21820	000-080-016		For MODEL1824C-BB/1834C-BB 20 m signal cable	
	CP03-21830	000-080-017		For MODEL1824C-BB/1834C-BB 30 m signal cable	
	CP03-22000	000-080-021	1	For 1934C-BB/1944C-BB/1954C-BB 10 m signal cable	
	CP03-22010	000-080-022		For 1934C-BB/1944C-BB/1954C-BB 15 m signal cable	
	CP03-22020	000-080-023		For 1934C-BB/1944C-BB/1954C-BB 20 m signal cable	
	CP03-22030	000-080-024		For 1934C-BB/1944C-BB/1954C-BB 30 m signal cable	
	CP03-24501	000-080-191	1	For 1954C, power supply unit	
Accessories	FP03-09301	000-852-297	1	For RCU-017	
Spare parts	SP03-14501	000-844-420	1set	Fuses for processor unit	
	SP03-14001	000-080-018	1set	Fuses for 1954C-BB's power supply unit	

Optional supply

Name	Type	Code No.	Qty	Remarks
Rectifier	PR-62	000-013-484	1	For GD-1920C-BB, 100 VAC
		000-013-485		For GD-1920C-BB, 110 VAC
		000-013-486		For GD-1920C-BB, 220 VAC
		000-013-487		For GD-1920C-BB, 230 VAC
	RU-3423	000-030-443	1	For MODEL series
External buzzer	XH3-BZ-L970	000-146-422	1	
Cable assy.	MJ-A6SPF0014-010	000-144-421	1	For NavNet, 1 m
	MJ-A6SPF0014-050	000-144-422	1	For NavNet, 5 m
	MJ-A6SPF0014-100	000-144-423	1	For NavNet, 10 m
	MJ-A6SPF0014-200	000-144-424	1	For NavNet, 20 m
	MJ-A6SPF0014-300	000-144-425	1	For NavNet, 30 m
	MJ-A6SPF0012-050	000-134-424	1	For navaid, 5 m, 6P-6P cross
	MJ-A6SPF0012-100	000-133-817	1	For navaid, 10 m, 6P-6P cross
	MJ-A6SPF0003-050	000-117-603	1	w/6P connector, 5 m
	MJ-A6SPF0009-100	000-125-236	1	w/6P connector, 10 m
	MJ-A6SPF0007-100	000-125-237	1	For compass, 10 m, 6P-6P straight
	MJ-A7SPF0007-050	000-144-418	1	w/7P connector, 5 m
	MJ-A6SRMD/TM11AP8-005	000-144-463	1	Adapter cable for HUB
	3COX-2P-6C 5M	000-146-500	1	For monitor D-sub 15
	3COX-2P-6C 10M	000-146-501	1	
	MJ-B24LPF0010-100	000-147-880	1	For remote display, 10 m
	MJ-B24LPF0010-200	000-147-881	1	For remote display, 20 m
	MJ-B24LPF0010-300	000-147-882	1	For remote display, 30 m
ARP kit	ARP-11	008-523-050	1	ARP Board, for radar
Mounting bracket (1)	OP03-92	008-445-070	1	For MODEL1834C-BB
Mounting bracket (2)	OP03-93	008-445-080	1	For MODEL1824C-BB
Chart card	-	-	-	Specify when ordering.
EMI core	CP03-24801	008-481-410	1	For remote display cable connection
Ring unit	MU3721	000-144-645	1	For trackball of control unit
Desktop mounting kit	FP03-09901	008-443-540	1	For control unit RCU-017
Cable assy.	MJA7SPF0006-050	000-147-879	1	Cable between processor unit and control unit
	MJA7SPF0006-100	000-147-578		Cable between processor unit and control unit
Control unit	RCU-017-E-5-CS	000-080-533	1	w/5 m cable
	RCU-017-E-5-CS	000-080-534	1	w/10 m cable


SYSTEM CONFIGURATIONS

All NavNet products incorporate a "network circuit board" to integrate each NavNet product on board through an optional LAN cable (Ethernet 10BASE-T). Each NavNet product is assigned an IP address to enable transfer of images between other NavNet products. For example, video plotter pictures can be transferred to a radar and vice versa. Pictures received via the NavNet may be adjusted at the receiving end.


The number of processor units which may be installed depends on the number of network sounders connected. For a system incorporating three or more NavNet products, a "hub" is required to process data.

For one network sounder: one radar and three plotters, or four plotters

For two network sounders: one radar and two plotters, or four plotters



NavNet system: Model 1824C-BB/1834C-BB/1934C-BB/1944C-BB/1954C-BB



NavNet system: GD-1920C-BB


Note: The output signal from the processor unit for a monitor is as follows.

RGB signal: Analog 0.7 Vpp, Output impedance 75 Ω

Synchro signal: H 31.5 kHz, V 60Hz (Separate), TLL level
(VGA signal)


Choose a monitor whose aspect ratio is 4:3, for example, VGA, SVGA, XGA, SXGAX, VXGA, QXGA, etc

Three-or-more-unit NavNet system



Three-or-more-unit NavNet system

Two-unit NavNet system



Two-unit NavNet system

This page intentionally left blank.

1. MOUNTING

1.1 Mounting the Control Unit

1.1.1 Mounting considerations

The control unit can be mounted on a desktop or flush mounted in a console or panel. For flush mounting, the optional flush mount kit is required.

When selecting a mounting location for the control unit keep the following in mind:


- Keep the control unit out of direct sunlight.
- The temperature and humidity at the mounting location should be moderate and stable.
- Locate the unit away from exhaust pipes and vents.
- The mounting location should be well ventilated.
- Mount the unit where shock and vibration are minimal.
- Keep the unit away from electromagnetic field generating equipment such as motors and generators.
- For maintenance and checking purposes, leave sufficient space at the sides and rear of the unit and leave slack in cables. Minimum recommended space is shown in the outline drawing for the control unit.
- A magnetic compass will be affected if the control unit is placed too close to it. Observe the compass safe distances shown in the SAFETY INSTRUCTIONS to prevent disturbance to the magnetic compass.

1.1.2 Mounting procedure

Flush mounting

Follow the procedure below to mount the control unit in a panel, using accessories FP03-10001.

1. Prepare a cutout in the mounting location, referring to the outline drawing at the end of this manual.
2. Set the control unit to the cutout.
3. Attach the mounting plate to the control unit with four screws M4 x 10 from the rear side.
4. Screw four wing bolts into wing nuts.
5. Fasten the control unit to the mounting location with four wing bolts and wing nuts assembled at step 4.




Flush mounting the control unit

6. Attach hard cover to protect the control unit.

How to remove the hard cover

Place your thumbs at the locations shown with circles in the illustration at right, and then lift the cover while pressing it with your thumbs.




Desktop mounting

Use the optional desktop mount kit FP03-09901 (Code number 008-443-540).

No.	Name	Type	Code No.	Qty
1	Hanger fixture	19-023-1061	100-307-941	1
2	Hanger fixture	19-023-1062	100-307-951	1
3	Tapping screw	5 x 20	000-802-081	4
4	Hex bolt	M5 x 10	000-802-288	2

1. Fix the hanger fixture 19-023-1062 on a desktop with four tapping screws (5x20).
2. Fix the hanger fixture 19-023-1061 to the rear panel of the control unit with four M4x10 (supplied as accessories).
3. Set the control unit to the hanger fixture 19-023-1062 fixed at step 1 and fit it with two hex bolts.



Desktop mounting of display unit

4. Attach hard cover to protect the control unit.


1.2 Mounting the Processor Unit

The unit can be mounted on the deck, a desktop or on a bulkhead. Select a mounting location considering the points below.

- Locate the unit out of direct sunlight.
- Select a location where temperature and humidity are moderate and stable.
- Consider the length of the cable connected among the processor unit, antenna unit (or power supply unit) and control unit.
- For mounting on a bulkhead, be sure the mounting location is strong enough to support the unit (4.1kg) under the pitching and rolling normally encountered on the vessel.
- Leave sufficient space around the unit for maintenance and servicing. Recommended maintenance space appears in the outline drawing at the back of this manual.
- A magnetic compass will be affected if the processor unit is placed too close to the magnetic compass. Observe the compass safe distances in the SAFETY INSTRUCTIONS to prevent disturbance to the magnetic compass.

Tabletop or deck mounting: Fasten with four tapping screws.

Bulkhead mounting: Mark four fixing hole positions on the bulkhead. Screw in two tapping screws at lower fixing positions, leaving 5 mm protruding. Set the processor unit to the screws and screw in two tapping screws at upper positions. Tighten all screws.




Processor unit, mounting dimensions

1.3 Mounting the Antenna Unit of MODEL1824C-BB

1.3.1 Mounting considerations

When selecting a mounting location for the antenna unit, keep in mind the following points.

- Install the antenna unit on the hardtop, radar arch or on a mast on an appropriate platform. (For sailboats, a mounting bracket is optionally available.) It should be placed where there is a good all-round view with, as far as possible, no part of the ship's superstructure or rigging intercepting the scanning beam. Any obstruction will cause shadow and blind sectors. A mast, for instance, with a diameter considerably less than the width of the antenna unit, will cause only a small blind sector. However, a horizontal spreader or crosstrees in the same horizontal plane would be a much more serious obstruction; place the antenna unit well above or below it.




Typical antenna unit placement on sailboat and powerboat

- In order to minimize the chance of picking up electrical interference, avoid where possible routing the antenna cable near other electrical equipment onboard. Also avoid running the cable in parallel with power cables.
- Observe the compass safe distances mentioned in the SAFETY INSTRUCTIONS to prevent interference to a magnetic compass.

1.3.2 Mounting procedure

1. Remove the mounting hardware from the bottom of the antenna unit: four each of hex bolts (M10X20), spring washers and flat washers. Save the mounting hardware to use it to fix the antenna unit to the mounting platform later on.



Antenna unit, showing location of mounting hardware


2. Construct a platform (wood, steel*, or aluminum) of 5-10 mm (recommended dimension) in thickness referring to the outline drawing at back of this manual. Fasten the platform to the mounting location. Next, position the mounting base on the platform so the cable entrance faces the stern direction.

*: For steel platform take appropriate measures to prevent corrosion.

Note: When drilling holes in the platform, be sure they are parallel with the fore and aft line.

3. Using the hex bolts, flat washers and spring washers removed at step 1, fasten the mounting base to the platform. **The torque should be between 19.6-24.5 N•m.**


Note: Longer hex bolts (M10X25) are supplied with the installation materials. Use them instead of the hex bolts removed earlier if the mounting platform thickness is 5–10 mm.




How to fasten the mounting base to platform

4. The mounting base is fitted with a snap holder, which may be used to hang the cover after removal. Use the hole next to a screw hole inside the cover to hang it.
 - a) Unfasten the snap assy. with the string attached at the holder in the mounting base.
 - b) Unwind the string.
 - c) Attach the snap to a screw hole on the inside of the cover.

Note: Do not hang any other objects with the snap.



5. Unfasten the rotation detector cable from the cable clamps, referring to the figure on page 1-11.
6. Unfasten 16 screws (①, ② and ③ in the figure below) to dismount the shield plate, core case and core case cover.




Caution: Be careful not to pinch the rotation detector cable when remounting the shield plate.

7. Pass the antenna cable with connector through the cable gland, gasket and cable entrance of the antenna unit, and then tighten cable gland.


Note 1: Be sure the shrink tube on the antenna cable does not contact the gasket.

Note 2: Pinch the gasket tightly and insert it into the cable entrance. Confirm that the slit in the gasket is completely closed after inserting it into the cable entrance.




Antenna unit, inside view

8. Twist antenna connector cables at the position between the shrink tube and the cable tie, and then attach EMI core (supplied) to cables as shown below. After attachment, shift EMI core slightly to confirm that it does not pinch cables.




9. Attach connectors of the antenna cable to the locations shown in the figure below, and then fasten a pan head screw M4x10 to fix shield cable and core case (removed at step 6.)




Antenna unit, connector location and fixing the shield cable w/core case

10. Put the EMI core on the antenna cable into the core case attached at step 9, with the flat side of the core facing downward.




EMI core, putting into core case

11. Refasten the shield plate and core case cover with 15 screws. Be sure that the cable from the rotation detector passes through the notch between the two cable ties.



How to pass the rotation detector cable

12. Pass the cable from the rotation detector through two cable clamps.



Antenna unit, clamping the rotation detector cable

13. Follow the instructions on the label inside the mounting base to secure the snap assy.

14. Confirm that the rubber gasket is properly positioned and that the triangle mark on the radome cover is aligned with the triangle mark on the mounting base, then tighten the fixing screws for the cover. See the sectional view on page 1-9 for how to position the rubber gasket.


Mounting the optional mounting bracket

A mounting bracket for fastening the antenna unit to a mast on a sailboat is optionally available.


Contents of mounting bracket 2 kit Type: OP03-93, Code No.: 008-445-080

Part	Type	Code No.	Qty
Hex. bolt	M4x12	000-804-725	4
Hex. bolt	M8x20	000-805-707	8
Mounting plate	03-018-9001-0	100-206-740	1
Support plate (1)	03-018-9005-0	100-206-780	1
Support plate (2)	03-018-9006-0	100-206-790	1
Bracket (1)	03-028-9101-0	100-206-810	1
Bracket (2)	03-028-9102-0	100-206-820	1
Fixing plate	03-028-9103-0	100-206-830	2

Assemble the mounting bracket and fasten it to a mast. Fasten the antenna unit to the bracket. For details, see the figure on the next page.



(A) Assembling the mounting bracket



(B) Fastening antenna to mounting bracket

How to assemble and mount the optional mounting bracket


1.4 Mounting the Antenna Unit of MODEL1834C-BB

1.4.1 Mounting considerations

- See the mounting considerations for the MODEL1824C-BB on page 1-5.

1.4.2 Mounting procedure

1. Open the antenna unit packing box carefully.
2. Unbolt the four bolts at the base of the radome cover to remove the cover.




The mounting surface must be parallel with the waterline and provided with five holes (four fixing holes and one cable entry) whose dimensions are shown in the outline drawing at the back of this manual.

The unit is adjusted so a target echo returned from the bow direction will be shown on the zero degree (heading line) position on the screen. When drilling holes, be sure they are parallel with the fore and aft line.


3. Prepare a platform (wood, steel*, or aluminum) of 5 to 10 millimeters in thickness for the antenna unit.

A mounting bracket for mounting the antenna unit on a sailboat mast is optionally available. (Refer to page 1-17.) Find the cable entry on the radome base. Next, position the radome base so the cable entry faces the stern direction. This alignment must be as accurate as possible.

*: For steel platform, take appropriate measures to prevent corrosion.




Antenna unit, cover removed



How to fasten the radome base to the mounting platform

Wiring and final preparations


4. Drill a hole of approx. 16 mm diameter through the deck or bulkhead to run the signal cable between the antenna unit and the display unit. (To prevent electrical interference avoid running the signal cable near other electrical equipment and in parallel with power cables.) Pass the cable through the hole. Then, seal the hole with sealing compound for waterproofing.
5. Remove two shield covers in the radome.
6. Remove the cable clamping plate by unfastening four screws and removing a gasket.




Antenna unit, inside view

7. Pass the cable through the hole at the bottom of the radome base.
8. Secure the cable with the cable clamping plate and gasket. Ground the shield wire by one of the screws of the cable clamping plate.


9. Attach three connectors of the signal cable to respective receptacles as shown below.



Signal cable, antenna unit side




10. Bundle the cables with the EMI core (supplied) as shown below.



EMI core

11. Fix the shield cover. Do not pinch the cable.

12. Attach the radome cover, aligning triangle mark on radome cover with that on radome base.



How to position the radome cover

13. Loosely fasten the radome fixing bolts. You will tighten them after confirming magnetron heater voltage.

Mounting the optional mounting bracket

A mounting bracket for fastening the antenna unit for the MODEL1834C-BB to a mast on a sailboat is optionally available.

Contents of mounting bracket 1 (Type: OP03-92, Code No.: 008-445-070)

Part	Type	Code No.	Qty
Hex. bolt	M4X12	000-804-725	4
Hex. bolt	M8X20	000-805-707	8
Mounting plate	03-018-9001-0	100-206-740	1
Support plate (1)	03-018-9005-0	100-206-780	1
Support plate (2)	03-018-9006-0	100-206-790	1
Bracket (1)	03-018-9002-1	100-206-751	1
Bracket (2)	03-018-9003-1	100-206-761	1
Fixing plate	03-018-9004-1	100-206-771	2


Assemble the mounting bracket and fasten it to a mast. Fasten the antenna unit to the bracket. For details, see the figure on page 1-11.

1.5 Mounting the Antenna Unit of MODEL1934C-BB/1944C-BB/1954C-BB


1.5.1 Mounting considerations

- The antenna unit is generally installed either on top of the wheelhouse or on the radar mast on a suitable platform. Locate the antenna unit where there is a good all-round view. Any obstruction will cause shadow and blind sectors. A mast for instance, with a diameter considerably less than the horizontal beamwidth of the radiator, will cause only a small blind sector, but a horizontal spreader or crosstrees in the same horizontal plane as the antenna unit would be a much more serious obstruction; you would need to place the antenna unit well above or below it.
- It is rarely possible to place the antenna unit where a completely clear view in all directions is available. Thus, you should determine the angular width and relative bearing of any shadow sectors for their influence on the radar at the first opportunity after fitting.
- To lessen the chance of picking up electrical interference, avoid where possible routing the signal cable near other onboard electrical equipment. Also avoid running the cable in parallel with power cables.
- A magnetic compass will be affected if the antenna unit is placed too close to it. Observe the compass safe distances mentioned in the SAFETY INSTRUCTIONS to prevent interference to a magnetic compass.
- Do not paint the radiator aperture, to ensure proper emission of the radar waves.
- When this radar is to be installed on larger vessels, consider the following points:
 - The signal cable run between the antenna and the display units comes in lengths of 10 m, 15 m, 20 m and 30 m.
 - Deposits and fumes from a funnel or other exhaust vent can adversely affect the aerial performance and hot gases may distort the radiator portion. The antenna unit must not be mounted where the temperature is more than 70°C.


As shown in the figure below, the antenna unit may be installed on the bridge, on a common mast or on the radar mast.



(a) On bridge



(b) Common mast



(c) Radar mast

Mounting methods



1.5.2 Mounting procedure

Referring to the outline drawing at the back of this manual, drill five holes in the mounting platform: four holes of 15 mm diameter for fixing the antenna unit and one hole of 25-30 mm diameter for the signal cable.

Fastening the radiator to the radiator bracket


For your reference, the antenna installation materials list appears in the packing list for this unit at the back of this manual.

1. Remove the radiator cap from the radiator bracket.
2. Coat contacting surface between the antenna radiator and the radiator bracket with silicone sealant as shown in the figure below.



Coating the antenna with silicone sealant

3. Coat threaded holes on the antenna radiator with silicone sealant.
4. Grease the O-ring and set it to the radiator bracket.
5. Lay the antenna radiator on the radiator bracket.
6. Coat the radiator fixing bolts (4 pcs.) with silicone sealant. Fasten the antenna radiator to the radiator bracket with the radiator fixing bolts, flat washers and spring washers.



Fastening the radiator bracket to the antenna unit chassis


Mounting the antenna unit

The antenna unit can be mounted using the fixing holes on the outside (200 x 200 mm) or inside (140 x 150 mm) the antenna unit.

Using outside fixing holes of the antenna housing


Use the hex head bolts (supplied) to mount the antenna unit as below.

1. Lay the corrosion-proof rubber mat (supplied) on the mounting platform.



Location of rubber mat

2. Lay the antenna unit on the mounting platform, orienting it as shown in below.



Antenna unit




CAUTION

Do not lift the Antenna unit by the radiator; lift it by the housing.


The radiator may be damaged.

3. Insert four hex bolts (M12x60, supplied) and seal washers (Φ30, supplied) from the top of the antenna housing, as shown below.



Fixing the antenna unit chassis


4. Pass flat washers (M12, supplied), spring washers (M12, supplied) and nuts (M12, supplied) onto hex bolts. Fasten by tightening nuts. Do not fasten by tightening the hex bolts; seal washers may be damaged.



How to fasten antenna unit to mounting platform

5. Coat flat washers, spring washers, nuts and exposed parts of bolts with anticorrosive sealant.
6. Prepare ground point in mounting platform (within 300 mm of ground terminal on antenna unit) using M6 x 25 bolt, nut and flat washer (supplied).
7. Run the ground wire (RW-4747, 340 mm, supplied) between the ground terminal and ground point.

8. Coat ground terminal and ground point with silicone sealant as shown below.




How to coat ground point and ground terminal with silicone sealant

Using inside fixing holes of the antenna housing

This method requires removal of the RF unit in the antenna unit to access inside fixing holes. Use hex head bolts, flat washers, spring washers and nuts (local supply) to mount the antenna unit, confirming length of bolts.

1. Unfasten four scanner bolts on the cover to open the antenna unit.
2. Unplug connector connected between upper and lower chassis.
3. Separate upper chassis from lower chassis by removing two hex head bolts (M8x25).
4. Remove the board cover by unfastening four pan head screws.
5. Remove connector from RF unit.
6. Remove RF unit by unfastening four hex head bolts.




Antenna unit chassis, upper chassis separated

7. Lay the corrosion-proof rubber mat (supplied) on the mounting platform.
8. Fasten the lower chassis to the mounting platform with hex head bolts, spring washers, flat washers and nuts (local supply), and then coat flat washers, nuts and exposed parts of bolts with silicone sealant. Cut a slit in the rubber bushing and insert bolt into the bushing. Do not use seal washers.
9. Reassemble RF unit, cover and chassis.
10. Set four knob caps (supplied) into outside fixing holes.
11. Do steps 6-8 in "Outside fixing holes".

Connecting the signal cable


Only the signal cable runs from the display unit (power supply unit in case of 1954C-BB) to the antenna unit. In order to minimize the chance of picking up electrical interference, avoid where possible routing the signal cable near other onboard electrical equipment. Also, avoid running the cable in parallel with power cables. Pass the cable through the hole and apply sealing compound around the hole for waterproofing.

1. Open the antenna cover by loosening four bolts, and then fix the stay.



Antenna unit chassis, cover opened


2. Unfasten the cable gland assembly (plate, gasket, flat washer).
3. Pass the signal cable with connector through the bottom of the antenna unit chassis. Pass the cable through the gland assembly as shown below.



Passing the signal cable through the cable gland assembly


4. Fasten the crimp-on lug on the shield to one of the fixing bolts of the cable gland assembly.

5. Position the signal cable so that no more than 4 cm of the sheath is exposed as shown in the figure below. Tighten fixing bolts.




How to fix signal cable in cable gland

6. Unfasten four screws shown in the figure below.




Antenna unit chassis, cover opened

7. Pass the signal cable through the cable protector.



Antenna unit chassis, cover opened


8. Connect the signal cable to the RTB Board (03P9249 or 03P9250), referring to the interconnection diagram and the figure below.
9. Attach three EMI cores to the signal cable as shown below.



Antenna unit chassis, cover opened

10. Fix the signal cable with the cable clamp.
11. Release the stay and close the cover. Loosely fasten the scanner bolts; you will have to make some adjustments inside after completion of wiring.

Note: When closing the cover, set the gaskets to grooves in the bottom chassis, then tighten bolts.




1.6 Mounting the Power Supply Unit for MODEL1954C-BB

A power supply unit is shipped with the MODEL1954C-BB, because of its high power consumption.

The power supply unit can be installed almost anywhere provided the location is dry, well-ventilated, sufficient maintenance space is provided and is installed within 5 m (cable length) from the display unit.


Note: Do not install the power supply unit on the overhead; install it on the deck or bulkhead.



This page intentionally left blank.

All wiring is terminated at the rear of the processor unit.

RSB-0094-0075	RSB-0071-057	XN10A-RSB-0070-064	XN12A-RSB-0070-059	XN12A-RSB-0072-060
		XN10A-RSB-0073-064	XN12A-RSB-0073-059	XN12A-RSB-0073-060
				XN13A-RSB-0072-060




Wiring

DJ-1

For MODEL1824C-BB/1834C-BB/1934C-BB/1944C-BB/1954C-BB, remove the waterproofing cap from the DJ-1 port on the processor unit and discard it.

GD-1920C-BB: Do not remove the waterproofing cap. Wrap the connector nut and cap with vinyl tape as shown below.



Waterproofing cap and connector nut, sectional view

DATA1 to DATA3

Other equipment can be connected to DATA1-DATA3 as shown below.

DATA1 (7P)	DATA2 (6P)	DATA3 (6P)
GPS receiver GP-310B/320B	NMEA sentence (ex. navaid)	Heading sensor (ex. SC-60/120) (MODEL series only)


This equipment can receive the following NMEA 0183 format sentence from external equipment. You will need the optional NMEA cable to connect with external equipment.

- Own ship's position: GGA>RMC>RMA>GLL
- Time: ZDA>RMC
- Ship's speed: RMC>RMA>VTG>VHW
- Other ship's information: TTM
- Wind speed and angle: MWV>VWT/VWR
- Heading (True): HDT>HDG>HDM>VHW
- Heading (Magnetic): HDM>HDG>HDT>VHW
- Course: RMC>RMA>VTG
- Depth: DPT>DBT>DBS>DBK
- Waypoint: RMB>WPL>BWR>BWC
- Water temperature: MTW
- Target data: TLL (output from VHF radiotelephone FM-2721)
- DSC information: DSC>DSE (output from VHF marine transceiver FM-3000)

Connecting GP-310B/320B to DATA 2 port

GPS receiver GP-310B/320B can be connected to DATA 2 port as shown below when port 1 is not available.

You need a junction box and optional cable MJ-A6SPF0003-050 or MJ-A6SPF0009-100.



Connecting GP-310B/320B to DATA 2 port


NETWORK port

Other NavNet equipment should be connected to this port with the optional MJ-A6SPF0014 cable. Available equipments are shown below.

Radar	Plotter	Network sounder	Other
1824C-BB/1834C-BB/ 1934C-BB/1944C-BB/ 1834C-BB/1954C-BB Or other FURUNO NavNet radar.	GD-1920C-BB	ETR-6/10N ETR-30N	HUB (used when more than two NavNet units are connected.)

2.2 Wiring the Power Supply Unit for MODEL1954C-BB


1. Loosen three M4 screws to remove the cable clamp.
2. Loosen six M4 screws to remove the unit cover.
3. Attach the VL connector of power supply cable VL3P-VV-S2X2C-AA050 (supplied as installation materials) to J1 on the POWER Board.
4. Attach the VH and NH connectors of MJ-B24LPF0009-050 cable (supplied as installation materials) to the appropriate locations; VH9: J3, VH4: J4, NH13: J5.



Power supply unit, cover removed

5. Lay two cables on the slots referring to the figure above.
6. Reattach the unit cover (removed at step 2).
7. Reattach the cable clamp (removed at step 1) to fix the two cables.
8. Connect the antenna cable to the ANT port on the power supply unit.
9. Connect the ground wire (local supply, IV-2sq) between the ground terminal and ship's ground.

Note: The power for the power supply unit and processor unit must be drawn from the same power switch on the ship's power terminal board.



Ship's power terminal board

Wiring processor unit and power supply board to power terminal board

Replacement of the fuse

The power supply unit is shipped with a 15 A fuse. Replace the 15 A fuse with a 7 A fuse (supplied) when the ship's battery is 24 VDC. The fuse in the processor unit is also 15 A. Replace it with a 3A fuse.


This page intentionally left blank.

3. SETTING UP THE EQUIPMENT

3.1 Setting up with the Installation Wizard


After you have installed the equipment, set up the equipment with the installation wizard. The wizard allows you to easily set up the NavNet network (choose source of radar, sounder and auxiliary), GPS, ports, etc.

1. Press the **POWER/TX** key to turn on the power, and the following screen appears.



Installation wizard, language selection window

2. Rotate the **ENTER** knob to choose the appropriate language and then push the C: ENTER soft key.
3. A dialog box asks you if you want to start the simulation mode, which provides simulated operation of the equipment.
4. Press the **CLEAR** key to skip the simulation mode. Then, the SELECT MODE window appears. When confirming connections only, the simple check mode is useful.



5. Confirm that INST. WIZARD is selected, and then push the A: ENTER soft key. A diagnostic test is conducted and then the chart disclaimer message appears.
6. You are then asked "LOAD SETTING DATA FROM CARD?". This allows you to use the set up this NavNet unit with the settings of another NavNet unit, thereby shortening the time required to set up the equipment. To use the settings of another NavNet unit, insert the appropriate SD card in the slot and push the **ENTER** knob. If not, hit the **CLEAR** key. If you loaded settings, the message "LOADING COMPLETED. REMOVE THE CARD AND PRESS ANY KEY TO RESTART" appears if loading was successful. Remove the card and press any key to restart the equipment; installation is completed. To set up manually, go to step 7.

CAUTION: Ensure that the settings to be loaded are compatible with this NavNet unit. Improper setting will damage the equipment.

7. The screen for set up of units of measurement appears.

► RANGE UNIT	nm, kt
DEPTH UNIT	ft
TEMPERATURE UNIT	°F
WIND UNIT	kt
LOCAL TIME OFFSET	+00:00

Installation wizard, units of measurement

8. Choose an item and then press the C: EDIT soft key. One of the following windows appears.

RANGE/SPEED UNIT	DEPTH UNIT	TEMPERATURE UNIT
▲ ☐ nm, kt ☒ km, km/h ☐ sm, mph ☐ nm & yd, kt ☐ nm & m, kt ☐ km & m, km/h ☐ sm & yd, mph ▼	▲ ☐ m ☒ ft ☐ fathoms ☐ PB ▼	▲ ☐ °C ☒ °F ▼
WIND SPEED UNIT ▲ ☐ kt ☒ km/h ☐ MPH ☐ m/s ▼	LOCAL TIME OFFSET +00:00	

9. Choose unit of measurement desired and then press the C: ENTER soft key. LOCAL TIME OFFSET allows you to use local time (instead of UTC time). Set the time difference between local time and UTC time.
10. After you have chosen units of measurement, press the A: NEXT soft key, and the NETWORK SETUP menu appears.

► DEVICE NUMBER	1
(HOST NAME	NAVNET-1)
(IP ADDRESS	172.031.003.003)
RADAR SOURCE	1
SOUNDER SOURCE	ETRO
AUX SOURCE	AUX1

Installation wizard, network setup

11. Choose appropriate item and then press the C: EDIT soft key. One of the following displays appears depending on your selection.

DEVICE NUMBER	RADAR SOURCE
▲	▲
○ 1 (IP:172.031.003.001)	○ 1 (IP:172.031.003.001)
○ 2 (IP:172.031.003.002)	○ 2 (IP:172.031.003.002)
○ 3 (IP:172.031.003.003)	○ 3 (IP:172.031.003.003)
○ 4 (IP:172.031.003.004)	○ 4 (IP:172.031.003.004)
▼	○ NO CONNECT
	▼

SOUNDER SOURCE	AUX SOURCE
▲	▲
○ ETR0 (IP:172.031.092.001)	○ AUX1 (IP:172.031.008.001)
○ ETR1 (IP:172.031.092.011)	○ AUX2 (IP:172.031.008.002)
○ ETR2 (IP:172.031.092.012)	○ AUX3 (IP:172.031.008.003)
○ ETR3 (IP:172.031.092.013)	○ AUX4 (IP:172.031.008.004)
○ ETR4 (IP:172.031.092.014)	○ OFF
○ ETR5 (IP:172.031.092.015)	▼
○ ETR6 (IP:172.031.092.016)	
○ ETR7 (IP:172.031.092.017)	
○ ETR8 (IP:172.031.092.018)	
○ ETR9 (IP:172.031.092.019)	
○ OFF	
▼	

12. Choose appropriate setting and then press the C: ENTER soft key.

If you set DEVICE NO. or RADAR SERVICE, turn the power on and off again at the completion of the installation wizard.

13. After choosing ALL sources, press the A: NEXT soft key, and the RADAR SETUP menu appears. **If you do not have a radar installed, go to step 33.**

▶ANTENNA TYPE	A
HEADING DATA	MAGNETIC
ANTENNA ROTATION	ROTATE
RADAR OPTIMIZATION	OFF
TIMING ADJUST	OFF
M. B. SUPPRESSION	OFF
RADAR ANTENNA HEIGHT	MEDIUM (3-10m, 10-33ft)
STC CURVE	MEDIUM
MONITOR MODE	OFF
HEADING ADJUST	OFF

Installation wizard, radar setup

14. Choose ANTENNA TYPE and then press the C: EDIT soft key.

ANTENNA TYPE
▲
○ A (MODEL 1824C-BB)
○ B (MODEL 1834C-BB)
○ C (MODEL 1934C-BB)
○ D (MODEL 1944C-BB)
○ E (MODEL 1954C-BB)
○ F (MODEL 1964C-BB)
▼

15. Choose the appropriate antenna type and then press the C: ENTER soft key.

16. Choose HEADING DATA and then press the C: EDIT soft key.

HEADING DATA
▲ ○ MAGNETIC ● TRUE ▼

17. Choose the appropriate heading data format and then press the C: ENTER soft key. Select MAGNETIC when connecting with a magnetic compass, or select TRUE when connecting with a gyrocompass.
18. Choose ANTENNA ROTATION and then press the C: EDIT soft key.

ANTENNA ROTATION
▲ ○ ROTATE ● STOP ▼

19. Choose ROTATE and then press the C: ENTER soft key. This lets you perform the various radar adjustments which follow.
20. Choose RADAR OPTIMIZATION and then press the C: EDIT soft key.


RADAR OPTIMIZATION
▲ ○ ON ● OFF ▼

21. Choose ON and then press the C: ENTER soft key. Then, the radar's video and tuning are automatically adjusted.
22. After optimization has been completed, choose TIMING ADJUST and then press the C: EDIT soft key.

TIMING ADJUST
▲ ○ ON ● OFF ▼

This adjustment ensures proper radar performance, especially on short ranges. The radar measures the time required for a transmitted echo to travel to the target and return to the source. The received echo appears on the display based on this time. Thus, at the instant the transmitter is fired, the sweep should start from the center of the display (sometimes called sweep origin.)

A trigger pulse generated in the display unit goes to the antenna unit through the signal cable to trigger the transmitter (magnetron). The time taken by the signal to travel up to the antenna unit varies, depending largely on the length of signal cable. During this period the display unit should wait before starting the sweep. When the display unit is not adjusted correctly, the echoes from a straight local object (for example, a harbor wall or straight pier) will not appear with straight edges – namely, they will be seen as “pushed out” or “pulled in” near the picture center. The range of objects will also be incorrectly shown.



Examples of improper and correct sweep timing

- Choose ON and then press the C: ENTER soft key.
- Transmit on the shortest range and confirm that gain and A/C SEA are properly adjusted.
- Visually select a target which forms straight line (harbor wall, straight piers).
- Rotate the **ENTER** knob to straighten the target selected at step b), and then press the **ENTER** knob to finish.

23. Choose M. B. SUPPRESSION and press the C: EDIT soft key.

M. B. SUPPRESSION
▲ ☐ ON ☒ OFF ▼

24. Choose ON and then press the C: ENTER soft key. Main bang is the “black hole” which appears at the display center on short ranges. Choosing ON will suppress the main bang.

25. Choose RADAR ANTENNA HEIGHT and then press the C: EDIT soft key.

RADAR ANT. HEIGHT
▲ ☐ HIGH (>10m, 33ft) ☒ MEDIUM (3-10m, 10-33ft) ☐ LOW (<10m, 33ft) ▼

26. Choose the height of the antenna above the water surface and then press the C: ENTER soft key.

27. Choose STC CURVE and then press the C: EDIT soft key.

STC CURVE
▲ ☐ NARROW ☒ NORMAL ☐ WIDE ▼

28. Choose appropriate STC curve setting and then press the C: ENTER soft key.

NARROW: The effective range of the A/C SEA adjustment is relatively short.

NORMAL: Between NARROW and WIDE.

WIDE: The effective range of the A/C SEA adjustment is relatively long.

29. If you are going to use the equipment as a remote display, choose MONITOR MODE and then press the C: EDIT soft key. If not, go to step 31.

MONITOR MODE
▲ ○ ON ⊙ OFF ▼

30. Choose ON and then press the C: ENTER soft key.

- TX blanking function is not available when the MONITOR MODE is ON. To set a TX blanking sector, select OFF from MONITOR MODE on the NavNet equipment, and then set the sector same as the main radar. Finally, set MONITOR MODE to ON.
- When the MONITOR MODE is ON, the following functions are not available.
 - Tuning (auto/manual, on the RADAR SETUP menu)
 - Antenna rotation (RADAR SETUP menu)
 - TX sector blanking (RADAR DISPLAY SETUP menu)
 - Watchman (RADAR DISPLAY SETUP menu)
 - Pulse select (Soft key)

31. Choose HEADING ADJUST and then press the C: EDIT soft key.

HEADING ADJUST
▲ ○ ON ⊙ OFF ▼

32. Choose ON and then press the C: ENTER soft key.

You have mounted the antenna unit facing straight ahead in the direction of the bow. Therefore, a small but conspicuous target dead ahead visually should appear on the heading line (zero degrees).

In practice, you will probably observe some small error on the display because of the difficulty in achieving accurate initial positioning of the antenna unit. The following adjustment will compensate for this error.

- a) Set ship's heading toward a suitable target (for example, ship or buoy) at a range between 0.125 and 0.25 nautical mile.
- b) Rotate the **ENTER** knob to bisect the target with the EBL.
- c) Press the ENTER soft key.
- d) As a final test, move the boat towards a small buoy and confirm that the buoy shows up dead ahead on the radar when it is visually dead ahead.

33. The next step is to choose navigation data sources and calibrate navigation data. Press the A: NEXT soft key to show the NAV SETUP menu.

► POSITION SOURCE	GP	
SPEED SOURCE	ETR	
TEMPERATURE SOURCE	ETR	
DETPH SOURCE	ETR	
STW CALIBRATION	+00%	
TEMP CALIBRATION	+00.0°F	
DEPTH CALIBRATION	+00ft	
WIND AVERAGING	001 seconds(s)	
WIND DIRECTION OFFSET	S000.0°	
WIND SPEED CALIBRATION	+00%	
STW 12.3 kt	TEMP 56.3°F	DEPTH 99.5ft
WIND SPEED 1.2 kt	WIND DIR 131°	

Installation wizard, nav setup

34. Choose item and press the C: EDIT soft key.
 35. Choose appropriate setting and then press the C: ENTER soft key. Refer to the table below for description of each item.

NAV SETUP menu description

Item	Description	Settings (Default in boldface)
Position Source	Chooses source of position data.	FURUNO BB GPS: GPS Receiver GP-310B/320B GP : GPS navigator (via NETWORK or NMEA port) LC: Loran C navigator (via NETWORK or NMEA port) ALL: Multiple navaid connection (via NETWORK or NMEA port)
Speed Source	Chooses source of speed data	ETR (NavNet sounder), NMEA
Temperature Source	Chooses source of water temperature data.	ETR , NMEA. Select ETR to show water temperature data fed from the network sounder.
Depth Source	Chooses source of depth data.	ETR , NMEA. Select ETR to show depth data fed from the network sounder.
STW Calibration	Calibrates NMEA speed data. Enter amount in percentage.	-50 to +50%, 00
Temp Calibration	Calibrates NMEA temperature data. Enter offset to correct NMEA temperature data.	-40.0°F to +40.0°F (or equivalent in °F), 00.0°F
Depth Calibration	Calibrates NMEA depth data. Enter offset to correct NMEA depth data.	-15 to +90 ft (or equivalent in ft, fathoms or P/B). 00 ft
Wind Averaging	Enter a value to smooth wind speed/direction data. Ship's bow is referenced to smooth wind vector movement.	001-600 s, 001 s
Wind Direction Offset	Offsets wind direction data.	S180°-P180°, S000.0°
Wind Speed Calibration	Offsets NMEA wind speed data. Enter amount in percentage.	-50 to +50%, 00%

36. After setting up navigation equipment, press the A: NEXT soft key, and the GPS SETUP menu appears. This menu sets up the FURUNO GPS receiver GP-310B/320B. **If you do not have this equipment, press the NEXT soft key and go to step 39.**

►GEODETIC DATUM	WGS-84
POSITION SMOOTHING	000 second (s)
SPD/CSE SMOOTHING	005 second (s)
LATITUDE OFFSET	0.000°N
LONGITUDE OFFSET	0.000°E
DISABLE SATELLITE	-- -- --
LATITUDE	45°35.000°N
LONGITUDE	125°00.000°W
ANTENNA HEIGHT	005 m
GPS FIX MODE	2D/3D
COLD START	NO

Installation wizard, GPS setup

37. Choose an item and press the C: EDIT soft key to show corresponding window.
 38. Choose setting and then press the C: ENTER soft key. Refer to the table which follows for description.

GPS SETUP menu description

Item	Description	Settings	Default Setting
Geodetic Datum	Your equipment is preprogrammed with most of the major chart systems of the world. Although the WGS-84 system, the GPS standard, is now widely used other categories of charts still exist. Select the chart system used, not the area where your boat is sailing.	Use the trackball or ENTER knob to select appropriate chart.	WGS-84
Position Smoothing	When the DOP or receiving condition is unfavorable, the GPS fix may change, even if the vessel is dead in water. This change can be reduced by smoothing the raw GPS fixes. A setting between 000 to 999 is available. The higher setting the more smoothed the raw data, however too high a setting shows response time to change in latitude and longitude. This is especially noticeable at high ship' speeds. Increase the setting if the GPS fix changes.	0-999 sec	0 sec (no position smoothing)

GPS SETUP menu description (con't from previous page)

Item	Description	Settings	Default Setting
Spd/Cse Smoothing	During position fixing, ship's velocity (speed and course) is directly measured by receiving GPS satellite signals. The raw velocity data may change randomly depending on receiving conditions and other factors. You can reduce this random variation by increasing the smoothing. Like with latitude and longitude smoothing, the higher the speed and course smoothing the more smoothed the raw data. If the setting is too high, however, the response to speed and course change slows. For no smoothing, enter all zeros.	0-999 sec	5 sec
Latitude Offset	Offsets latitude position to further refine position accuracy. Use the N <- - > S soft key to switch coordinate.	9.999'S – 9.999'N	0.0' (no offset)
Longitude Offset	As above but for longitude. Use the W <- - > E soft key to switch coordinate.	9.999'E – 9.999'W	0.0' (no offset)
Disable Satellite	Every GPS satellite is broadcasting abnormal satellite number (s) in its Almanac, which contains general orbital data about all GPS satellites, including those which are malfunctioning. Using this information, the GPS receiver automatically eliminates any malfunctioning satellite from the GPS satellite schedule. However, the Almanac sometimes may not contain this information. If you hear about a malfunctioning satellite from another source, you can disable it manually. Enter satellite number (max. 3 satellites) in two digits and press the ENTER soft key.		None
Latitude	Set initial latitude position after cold start. Use the N <- - > S soft key to switch coordinate.	90°S - 90°N	45°35.000'N
Longitude	Set initial longitude position after cold start. Use the W <- - > E soft key to switch coordinate.	180°E – 180°W	125°00.000W
Antenna Height	Enter the height of the GPS antenna unit above sea surface.	0-99 m	5 m

GPS SETUP menu description (con't from previous page)

Item	Description	Settings	Default Setting
Fix Mode	Choose position fixing method: 2D (three satellites in view), 2D/3D (three or four satellites in view whichever is greater).	2D, 2D/3D	2D/3D
Cold Start	Clears the Almanac to receive the latest Almanac.	No, Yes	No

WAAS setup

Press the D: WAAS SETUP soft key at the GPS SETUP menu to show the WAAS SETUP display.

Contents of WAAS SETUP menu

Item	Description	Settings	Default Setting
WAAS Mode	Select ON to use the WAAS mode.	On, Off	Off
WAAS Search	WAAS satellite can be searched automatically or manually. For manual search, enter appropriate WAAS satellite number.	Auto, Manual	Auto
WAAS Alarm	When the WAAS signal is lost, the audible alarm sounds with the visual message "NO WAAS SIGNAL." On: Alarm continues to sound until the WAAS positioning mode is available again or the alarm is recognized by key operation. Off: Alarm sounds three times.	On, Off	Off
Corrections Data	Selects the type of message for WAAS correction. Use "00" (operational status) in North America; "02" in other locations.	00 to 27, 99	02

39. After you have finished setting up the GPS receiver, it's now time to set up external equipment. Press the A: NEXT soft key to show the GPS/PORT menu. It is only necessary to set up ports which you are going to use; skip unnecessary steps. **If you do not have external equipment connected to the NavNet, press the NEXT key several times to show the "FINISH AND EXIT INSTALLATION WIZARD" screen and then push the ENTER knob to finish.**

► OUTPUT FORMAT	NMEA0183 Ver 2.0
LAT/LON FORMAT	DD'MM.MMM'
OUTPUT DESTINATION	NO

Installation wizard, GPS/PORT port setup

40. Choose item and press the C: EDIT soft key. Choose appropriate setting and then press the ENTER soft key. Refer to the table and sentence description on the next page for details.
41. Press the A: NEXT soft key, and the NMEA PORT menu appears. Set up this port similar to how you set up the GPS/PORT menu.

► OUTPUT FORMAT	NMEA0183 Ver 2.0
BAUD RATE	4800bps
LAT/LON FORMAT	DD°MM.MMM'
OUTPUT DESTINATION	NO

Installation wizard, NMEA port setup

Description of items in “port” menus

Item	Description	Settings	Default Setting
FURUNO GPS Sensor	Selects whether the GPS Receiver GP-310B/320B is connected to the DATA1 or DATA2 port or not.	Yes, No	Yes (DATA1) No (DATA2)
Output Format	Selects NMEA output version for the equipment connected.	NMEA0183 Ver. 1.5, NMEA0183 Ver. 2.0	NMEA0183 Ver. 2.0
Baud Rate	Sets baud rate.	(PC) 4800, 9600, 19200/(NMEA) Auto, 4800, 38400	4800 bps
Lat/Lon Format	Selects latitude/longitude format to output.	DD°MM.MM', DD°MM.MMM', DD°MM.MMMM'	DD°MM.MMM'
Output Destination	Selects whether to output route (data sentence RTE) and waypoint data (data sentence WPL) when destination is set.	Yes, No	No
PORT MNTR (soft key)	Use this key to view which sentences are being output. See the example below.		

```
$GPGLL,3415.2345,N,13520.5301,E,152500.00
,A*E7<CR><LF>$GPGLL,3415.2345,N,135
20.5301,E,152500.00,A*E7<CR><LF>$GPGLL
,3415.2345,N,13520.5301,E,152500.00,A*
E7<CR><LF>$GPGLL,3415.2345,N,13520.530
1,E,152500.00,A*E7<CR><LF>$GPGLL,3415.
2345,N,13520.5301,E,152500.00,A*E7<CR>
<LF>$GPGLL,3415.2345,N,13520.5301,E,15
2500.00,A*E7<CR><LF>
```

Installation wizard, port monitor display

42. Press the A: NEXT soft key, and the NMEA sentence selection window (for network) appears.

▶ AAM	--
APB	--
BOD	--
BWR	--
DPT	--
GGA	--
GLL	--
GTD	--
MTW	--
RMA	--
RMB	--
RMC	--
VHW	--
VTG	--
WPL	--
XTE	--
ZDA	--
HDT	--
HDG	--
MWV	--
ZTG	--

Installation wizard, NMEA sentence selection window

43. Choose sentence to process and press the A: ON/OFF soft key to show ON or “-” (OFF) as appropriate.

44. Press the A: NEXT soft key and the message “FINISH AND EXIT INSTALLATION WIZARD. ARE YOU SURE?” appears. Press the **ENTER** knob to finish the installation wizard.

This concludes the Installation Wizard. Turn off the equipment to register settings.

3.2 Checking Magnetron Heater Voltage

Magnetron heater voltage is formed on the MD (1824C-BB), PTU (1834C-BB) or RTB (1934C/1944C/1954C-BB) Board of the antenna unit, and preadjusted at the factory. Therefore, no adjustment is required. However, check magnetron heater voltage for confirmation as shown below. ***This procedure should only be performed by a qualified technician.***

1. Open the antenna unit.
2. Turn on the power. Do not transmit the radar.
3. Connect a multimeter, set to 10VDC range, appropriate position on the MD (1824C-BB), PTU (1834C-BB) or RTB (1934C-BB/1944C-BB/1954C-BB) Board in the antenna unit. Refer to the table in below.
4. Confirm that the multimeter indication is within the ratings shown below.

	MODEL1824C-BB	MODEL1834C-BB	MODEL1934C-BB/ 1944C-BB/1954C-BB
Check point	TP804#6 (+) and #4 (-) on MD Board	TP802#4 (+) and #6 (-) on PTU Board	J825#4 and #6 (GND) on RTB Board
Multimeter indication	7.9 to 8.1 V	7.4 to 7.6 V	7.4 to 7.6 V
Adjustment point	VR801 on MD Board	R106 on PTU Board	VR801 on MD Board

This page intentionally left blank.

4. OPTIONAL EQUIPMENT

4.1 External Buzzer


The external buzzer provides a louder alert when the alarm is violated.

External buzzer

Type: XH3-BZ-L970

Code no.: 000-146-422

1. Unfasten 11 screws and 9 connectors to remove the cover.
2. Use a knife to cut a “cross” in the rubber bushing on the rear cover.
3. Pass the 3P connector of the buzzer assembly through the rubber bushing from the outside of the cover.
4. Connect the 3P connector to J307 on the 19P1013 board. See below.
5. Close the cover.
6. Fix the buzzer within 1 m from the processor unit with two tapping screws.



Processor unit (cover removed)

4.2 ARP Kit ARP-11

Necessary parts


Name: ARP kit
Type: ARP-11
Code no.: 008-523-050

Contents of ARP kit


Name	Type	Code No.	Qty
ARP Board	18P9013	008-521-830	1
Pan head screw	M3x6 C2700W	000-881-403	4
Spacer*	SQ9	000-801-850	1
	SQ15	000-801-779	3
Spring washer*	M3 C5191W	000-864-204	3

*Not used

1. Unfasten 11 screws and 9 connectors to remove the cover.
2. Disconnect P1361 and P1357 from the 19P1015 board and unfasten six screws to remove the 19P1015 board and shield plate.



3. Mate P107 on the ARP Board to J112 on the 19P1001 board and fasten the ARP board with four screws.



19P1001 board
J112






4. Mount the shield plate and the 19P1015 board and connect P1361 and P1357 to the 19P1015.
5. Reassemble the processor unit.

PACKING LIST

19AV-X-9853 -1 1/1

RPU-015-E-* -CS

A-1

N A M E	O U T L I N E	DESCRIPTION/CODE №	Q'TY
ユニット	UNIT		
制御部 PROCESSOR UNIT		RPU-015-E-N 000-088-224 **	1
予備品	SPARE PARTS		
予備品 SPARE PARTS		SP03-14501 008-444-420	1
工事材料	INSTALLATION MATERIALS	CP03-25900	
工事材料 INSTALLATION MATERIALS		CP03-25901 008-443-690	1
ケーブル組品MJ CABLE ASSY.		MJ-A3SPF0018-050Z 000-139-872	1
図書	DOCUMENT		
ヒューズ 変更のお願い NOTICE FOR FUSE REPLACEMENT		C32-00007-* 000-809-188	1
操作要領書(英) OPERATOR'S GUIDE		OSE-35490-* 000-151-807	1
装備要領書(英) INSTALLATION MANUAL		IME-35490-* 000-151-806	1
取扱説明書(英) OPERATOR'S MANUAL		OME-35490-* 000-151-805	1

コード番号末尾の[**]は、選択品の代表型式/コードを表します。
CODE NUMBER ENDING WITH "**" INDICATES THE CODE NUMBER OF REPRESENTATIVE MATERIAL.

(略図の寸法は、参考値です。 DIMENSIONS IN DRAWING FOR REFERENCE ONLY.)



19AV-X-9853

PACKING LIST

19AV-X-9854 -0 1/1

RPU-015*/RCU-017E*

A-2





N A M E	O U T L I N E	DESCRIPTION/CODE №	Q'TY
ユニット	UNIT		
操作部一式箱詰品 CONTROL UNIT COMPLETE SET		RCU-017-E-5-CS 000-050-533 **	1
制御部一式箱詰品 PROCESSOR UNIT COMPLETE SET		RPU-015-E-N-CS 000-088-215 **	1

(略図の寸法は、参考値です。 DIMENSIONS IN DRAWING FOR REFERENCE ONLY.)

19AV-X-9854

PACKING LIST

RSB-0071-057

NAME	OUTLINE	DESCRIPTION/CODE No.	Q'TY
ユニット UNIT			
(完) 空中線部 ANTENNA UNIT		RSB-0071-057 000-086-830	1
空中線部工材 ANTENNA UNIT INSTALLATION MATERIALS		CP03-16901	
EMCコア EMC CORE		E04SS251512 000-144-673	1
六角ボルト 刈割 HEX. BOLT (SLOTTED HEAD)		M10X25 SUS304 000-862-308	4
ミカキ平座金 FLAT WASHER		M10 SUS304 000-864-131	4
スプリング座金 SPRING WASHER		M10 SUS304 000-864-261	4


注記)

DWG NO.
C3502-Z02- B

(略図の寸法は、参考値です。 DIMENSIONS IN DRAWING FOR REFERENCE ONLY.)

P A C K I N G L I S T





RSB-0094-075

N A M E		O U T L I N E		DESCRIPTION/CODE No.		Q' TY	
ユニット		UNIT					
空中線部				RSB-0094-075		1	
ANTENNA UNIT				000-080-237			
工事材料		INSTALLATION MATERIALS		CP03-25401			
六角ボルト スリ割				M10X25 SUS304		4	
HEX. BOLT (SLOTTED HEAD)				000-862-308			
EMIコア				RFC-10		1	
EMI CORE				000-141-085			

(略図の寸法は、参考値です。 DIMENSIONS IN DRAWING FOR REFERENCE ONLY.)

P A C K I N G L I S T

XN10A, XN12A

N A M E	O U T L I N E	DESCRIPTION/CODE No.	Q' T Y
ユニット	UNIT		
アンテナ ANTENNA	 L=1036 (XN10A), 1255 (XN12A).	XN10A, 12A 008-523-***	1
アンテナ工材	ANTENNA INSTALLATION MATERIALS	CP03-22901	
リング O-RING	 φ 80	JISB2401-1A-G80 000-851-313	1
スリーボンド SEALANT	 140 35	1211 50G 000-854-118	1
六角ボルト スリワリ HEX. BOLT	 30 φ 8	M8X30 SUS304 000-862-151	4
ミガキ平座金 FLAT WASHER	 φ 17	M8 SUS304 000-864-130	4
バネ座金 SPRING WASHER	 15	M8 SUS304 000-864-262	4





DWG NO.

C3500-Z01- C

(略図の寸法は、参考値です。 DIMENSIONS IN DRAWING FOR REFERENCE ONLY.)

FURUNO

CODE NO.		19AL-X-9401-1
TYPE		1/1

工事材料表 INSTALLATION MATERIALS		Model 1824C-BB/1834C-BB			
番号 NO.	名称 NAME	略図 OUTLINE	型名／規格 DESCRIPTIONS	数量 Q'TY	用途／備考 REMARKS
1	ケーブル組品MJ CABLE ASSY.	 L=10M	MJ-B24LPF0002-100	1	選択 TO BE SELECTED
			CODE NO. 000-138-972		
2	ケーブル組品MJ CABLE ASSY.	 L=15M	MJ-B24LPF0002-150	1	選択 TO BE SELECTED
			CODE NO. 000-138-970		
3	ケーブル組品MJ CABLE ASSY.	 L=20M	MJ-B24LPF0002-200	1	選択 TO BE SELECTED
			CODE NO. 000-138-974		
4	ケーブル組品MJ CABLE ASSY.	 L=30M	MJ-B24LPF0002-300	1	選択 TO BE SELECTED
			CODE NO. 000-138-973		

 DWG NO.
C3502-M01- B

FURUNO ELECTRIC CO., LTD.

(略図の寸法は、参考値です。 DIMENSIONS IN DRAWING FOR REFERENCE ONLY.)

FURUNO

FURUNO





CODE NO.		19AL-X-9402 -1
TYPE		

1/1

工事材料表

INSTALLATION MATERIALS

Model 1934C-BB/1944C-BB/1954C-BB

番号 NO.	名 称 NAME	略 図 OUTLINE	型名／規格 DESCRIPTIONS	数量 Q'TY	用途／備考 REMARKS
1	ケーブル組品MJ CABLE ASSY.	 L=10M	MJ-B24LPF0005-100	1	選択 TO BE SELECTED
			CODE NO. 000-140-434		
2	ケーブル組品MJ CABLE ASSY.	 L=15M	MJ-B24LPF0005-150	1	選択 TO BE SELECTED
			CODE NO. 000-140-435		
3	ケーブル組品MJ CABLE ASSY.	 L=20M	MJ-B24LPF0005-200	1	選択 TO BE SELECTED
			CODE NO. 000-140-436		
4	ケーブル組品MJ CABLE ASSY.	 L=30M	MJ-B24LPF0005-300	1	選択 TO BE SELECTED
			CODE NO. 000-140-437		

DWG NO.






C3504-M01- B

FURUNO ELECTRIC CO., LTD.

(略図の寸法は、参考値です。 DIMENSIONS IN DRAWING FOR REFERENCE ONLY.)

FURUNO

CODE NO.	008-503-360	03FR-X-9401-7
TYPE	CP03-18401	1/2

工事材料表 INSTALLATION MATERIALS					
番号 NO.	名称 NAME	略図 OUTLINE	型名/規格 DESCRIPTIONS	数量 Q'TY	用途/備考 REMARKS
1	シールワッシャ SEAL WASHER		03-001-3002-0	4	
			CODE NO. 300-130-020		
2	防蝕ゴム CORROSION-PROOF RUBBER MAT		03-142-3001-0	1	
			CODE NO. 100-275-580		
3	キャップ CAP		040-4010	4	
			CODE NO. 000-515-332		
4	六角ナット 1種 HEX. NUT		M12 SUS304	4	
			CODE NO. 000-863-112		
5	ミガキ平座金 FLAT WASHER		M12 SUS304	4	
			CODE NO. 000-864-132		
6	ハネ座金 SPRING WASHER		M12 SUS304	4	
			CODE NO. 000-864-263		
7	六角ボルト (全ネジ) HEX. BOLT		M12X60 SUS304	4	
			CODE NO. 000-862-191		
8	六角ナット 1種 HEX. NUT		M6 SUS304	1	
			CODE NO. 000-863-109		
9	ミガキ平座金 FLAT WASHER		M6 SUS304	3	
			CODE NO. 000-864-129		
10	ハネ座金 SPRING WASHER		M6 SUS304	1	
			CODE NO. 000-864-260		

DWG NO.



C3459-M02- G

FURUNO ELECTRIC CO., LTD.

(略図の寸法は、参考値です。 DIMENSIONS IN DRAWING FOR REFERENCE ONLY.)

FURUNO

CODE NO.	008-503-360	03FR-X-9401-7 2/2
TYPE	CP03-18401	

工事材料表 INSTALLATION MATERIALS					
番号 NO.	名称 NAME	略図 OUTLINE	型名／規格 DESCRIPTIONS	数量 Q'TY	用途／備考 REMARKS
11	六角ボルト HEX. BOLT		M6X25 SUS304	1	
			CODE NO. 000-862-180		
12	EMIコア EMI CORE		RFC-13	3	
			CODE NO. 000-141-084		
13	アース線 GROUNDING WIRE		RW-4747-1 03S4747	1	
			CODE NO. 000-566-000		

DWG NO.

C3459-M04- G

FURUNO ELECTRIC CO., LTD.

(略図の寸法は、参考値です。 DIMENSIONS IN DRAWING FOR REFERENCE ONLY.)






PACKING LIST

19AN-X-985

1/1

PSU-005

A-10

N A M E	O U T L I N E	DESCRIPTION/CODE No	Q 'TY
ユニット	UNIT		
空中線電源部 POWER SUPPLY UNIT		PSU-005 000-080-190	1
予備品	SPARE PARTS	SP03-14001	
ヒューズ FUSE		FGBO 7A AC125V 000-549-013	3
ヒューズ FUSE		FGBO 15A AC125V 000-549-014	3
工事材料	INSTALLATION MATERIALS	CP03-24501	
+トラスタップ ンネジ SELF-TAPPING SCREW		4X16 SUS304 1ｼﾂ 000-802-080	4
その他工材	OTHER INSTALLATION MATERIALS		
ケーブル組品MJ CABLE ASSY.		MJ-B24LPF0009-050 000-145-887	1
ケーブル組品 CABLE ASSY.		VL3P-VV-S2X2C-AA050 000-152-217	1

(略図の寸法は、参考値です。 DIMENSIONS IN DRAWING FOR REFERENCE ONLY.)

19AN-X-9851





表 1 TABLE 1

寸法区分 (mm) DIMENSIONS	公差 (mm) TOLERANCE
L ≤ 50	± 1.5
50 < L ≤ 100	± 2.5
100 < L ≤ 500	+3



注記 1) #印寸法は最小サービスクラック寸法とする。

2) 指定外の寸法公差は表 1 による。

3) 取付用ネジは＋トラスタップピンネジ呼び径5×20を使用のこと。

1. #: MINIMUM SERVICE CLEARANCE.

2. TABLE 1 INDICATES TOLERANCE OF DIMENSIONS WHICH IS NOT SPECIFIED.

3. USE SELF-TAPPING SCREWS 5x20 FOR FIXING THE UNIT.





DRAWN	Jun. 12, '05	E. MIYOSHI				
CHECKED	TAKAHASHI, T				TITLE	RPJ-015
APPROVED	Y. Hatai				名称	制御部 (卓上装備)
SCALE	1/4	MASS ±10% 4.1 kg			外寸	図
DWG No.	C.3550-G01-A				NAME	PROCESSOR UNIT (TABLETOP MOUNT)
						OUTLINE DRAWING

表 2 TABLE 2

MODEL	MASS (kg ±10%)
RSB-0087/0087A/110	4.9
RSB-0094	5.2
RSB-0095	5.1

表 1 TABLE 1

寸法区分(mm)	公差(mm)
DIMENSIONS	TOLERANCE
0 < L ≤ 50	±1.5
50 < L ≤ 100	±2.5
100 < L ≤ 500	±3



注記 1) 指定外の寸法公差は表 1 による。





2) 取付はM10 ボルトを使用のこと。
ネジ長さは板厚に依りて、20 (t≤5) または 25 (5<t≤10) とする。

NOTE 1. TABLE 1 INDICATES TOLERANCE OF DIMENSIONS WHICH IS NOT SPECIFIED.
2. USE M10 BOLTS FOR FIXING UNIT.
SCREW LENGTH SHALL BE ACCORDING TO PLATFORM THICKNESS:
20 (t≤5) OR 25 (5<t≤10).

DRAWN	Model 12-95 E. MIYOSHI	MODEL 1724C	TITLE	RSB-0087/0087A/0094/0095/110
CHECKED	TAKAHASHI, T	MODEL 1715	名称	空中線部
APPROVED	Y. Hatai	MODEL 1823C	外寸図	
SCALE	1/6	MODEL 1722/1722C/1723C	NAME	ANTENNA UNIT
DWG No.	C3489-G02-H	03-161-100G-3/03-164-300G-1	OUTLINE DRAWING	

表1 TABLE 1

寸法区分(mm) DIMENSIONS	公差(mm) TOLERANCE
$0 < L \leq 50$	± 1.5
$50 < L \leq 100$	± 2.5
$100 < L \leq 500$	± 3
$500 < L \leq 1000$	± 4



注記
指定外の寸法公差は表1による。

NOTE
TABLE 1 INDICATES TOLERANCE OF DIMENSIONS WHICH IS NOT SPECIFIED.

DRAWN Feb. 3, '05 E. MIYOSHI	MODEL 1734C MODEL 1834C/1834C(-BB)	TITLE RSB-0071
CHECKED TAKAHASHI, T	MODEL 1833/1833C MODEL 1732/1732C	名称 空中線部
APPROVED Y. Hatai	RS-1000 MODEL 1832	外寸図
SCALE 1/10	MASS 8 $\pm 10\%$ kg	NAME ANTENNA UNIT
DWG.No. C3441-G01-G	03-136-6001-G2	OUTLINE DRAWING

品 类

表 1 TABLE 1





種類	TYPE	XN10A	XN12A
空中線長(A)		1036±10	1255±10
ANT. LENGTH (mm)			
回転安全空間(B)		1200	1400
ANT. CLEARANCE (mm)			
質量(kg)		22	23
MASS(±10%)			

表 1 TABLE 1

- 1) 指定外寸法公差は表2による。
- 2) 取付はM12ボルトを使用のこと。
- 3) 本機取付台にφ25-30のケール貫通穴を開ける。

NOTE

1. TABLE 2 INDICATES TOLERANCE OF DIMENSIONS WHICH IS NOT SPECIFIED.
2. USE M12 BOLTS FOR FIXING THE UNIT.
3. MAKE A HOLE $\varnothing 25-30$ ON MOUNTING MAST FOR CABLE PASS.



DRAWN	Jan. 12, '05 E. MIYOSHI	MODEL 1934C-BB/1944C-BB	TITLE	RSB-0070/0073
CHECKED	TAKAHASHI, T	MODEL 1934C/1944C/1954C	名称	空中線部
APPROVED	Y. Hatai	MODEL 1933OR		外寸図
SCALE	1/10	MODEL 1933	NAME	ANTENNA UNIT
DWG. NO.	C3500-G01-D	MODEL 1762/C		MULTI INF. DRAWING

取付寸法 (矢印A)
FIXING DIMENSIONS (VIEW A)

取付穴 (標準)
M12x60 4-φ15
FIXING HOLE

ø25-30 ケーブル貫通式
HOLE FOR CABLE PASS

200
100
92
200 ± 0.5

表 1 TABLE 1

寸法範囲 (mm) DIMENSIONS	公差 (mm) TOLERANCE
0 < L ≤ 50	±1.5 mm
50 < L ≤ 100	±2.5 mm
100 < L ≤ 500	±3 mm
500 < L ≤ 1000	±4 mm
1000 < L ≤ 2000	±5 mm




表 2 TABLE 2

種類 TYPE	XN12A	XN13A
空中線長 (A) ANT. LENGTH (mm)	1255±10	1795±10
安全空間 (B) ANT. CLEARANCE (mm)	1400	1940
質量 (kg) MASS	23	25

- 注記
- 1) 指定外寸法公差は表1による。
 - 2) 取付はM12ボルトを使用のこと。
 - 3) 空中線部の取付台にφ25-30のケーブル貫通穴を開ける。
 - 4) 初期製造分は取付寸法240×240で出荷しております。
- 換装時に注意してください。


NOTE

1. TABLE 1 INDICATES TOLERANCE OF DIMENSIONS WHICH IS NOT SPECIFIED.
2. USE M12 BOLTS FOR FIXING UNIT.
3. MAKE A HOLE φ25-30 IN MOUNTING MAST FOR CABLE ENTRY.
4. NOTE FOR REPLACEMENT: FIXING HOLE DIMENSIONS ARE CHANGED FROM 240×240 OF PREVIOUS SETS TO 200×200.


取付部詳細
DETAIL FOR FIXING

DRAWN	Jan. 26, '05	E. MIYOSHI	MODEL 1964C/1964C-3B	TITLE	RSB-0070/0072/0073 (XN12A/13A)
CHECKED		TAKAHASHI, T	FR-704R/12	名称	空中線部
APPROVED		Y. Hatai	FR-704S-1000C	外寸図	
SCALE	1/10	MASS表2を参照 SEE TABLE 2	MODEL 1942R2 FR-7062/7112/7252	NAME	ANTENNA UNIT
DWG No.	C3459-G03-E			03-142-3000-G3	OUTLINE DRAWING

FURUNO ELECTRIC CO., LTD.



- 注 記 1) #印寸法は最小サービス空間寸法とする。
 2) 指定外の寸法公差は表 1 による。
 3) 取付用ネジは+トラスタッピンネジ呼び径4×16を使用のこと。

- NOTE 1. # MINIMUM SERVICE CLEARANCE.
 2. TABLE 1 INDICATES TOLERANCE OF DIMENSIONS WHICH IS NOT SPECIFIED.
 3. USE SELF-TAPPING SCREWS 4x16 FOR FIXING THE UNIT.


DRAWN Dec. 8, '02	E. MIYOSHI		TITLE PSU-005
CHECKED	TAKAHASHI, T	MODEL 1954C-BB	名称 電源部
APPROVED	Y. Hatai	MODEL 1954C MODEL 1953C	外寸図
SCALE 1/3	MASS 1.9 ±10% kg		NAME POWER SUPPLY UNIT
DWG.No. C3512-G01- B	19-022-200G-2		OUTLINE DRAWING

A

B

C

D



注 記
* 1) 造船所手配
* 2) コネクタは工場にて取付済み。
* 3) シールドは両ユニット側で完全に接地すること。
* 4) 副指示器として使用する場合は、制御部の内部設定を変更する。

NOTE
*1. SHIPYARD SUPPLY.
*2. CONNECTOR PLUG FITTED AT FACTORY.
*3. SHIELD SHOULD BE EFFECTIVELY GROUNDED AT BOTH UNIT ENDS.
*4. CHANGE SETTING IN PROCESSOR UNIT FOR USING AS A REMOTE DISPLAY.


DRAWN Jan. 25, '05 D. MILLS		TYPE MODEL 1824C-BB/1834C-BB
CHECKED TAKAHASHI . T		名 称 船舶用レーダー
APPROVED Y. Hatai		相互結線図
SCALE MASS kg		NAME MARINE RADAR
DWG. No. C3549-C01- A		INTERCONNECTION DIAGRAM

A

B

C

D




DRAWN Jan. 25, '05 D. MILLS		TYPE MODEL 1934C-BB/1944C-BB
CHECKED TAKAHASHI.T		名称 船舶用レーダー
APPROVED Y. Hatai		相互結線図
SCALE MASS kg		NAME MARINE RADAR
DWG. No. C3551-C01- A		INTERCONNECTION DIAGRAM

A

B

C

D



注 記

* 1) 造船所手配

* 2) コネクタは工場にて取付済み。

* 3) シールドは両ユニット側で完全に接地すること。

* 4) 副指示器として使用する場合は、指示器の内部設定を変更する。

NOTE

*1. SHIPYARD SUPPLY.

*2. CONNECTOR PLUG FITTED AT FACTORY.

*3. SHIELD SHOULD BE EFFECTIVELY GROUNDED AT BOTH UNIT ENDS.

*4. CHANGE SETTING IN THE DISPLAY UNIT FOR USING AS A REMOTE DISPLAY.


DRAWN	Feb. 2, '05 D. MILLS	TYPE	MODEL 1954C-BB
CHECKED	TAKAHASHI . T	名 称	船舶用レーダー
APPROVED	Y. Hatai		相互結線図
SCALE	MASS kg	NAME	MARINE RADAR
DWG. No.	C3553-C01- A		INTERCONNECTION DIAGRAM

A

B

C

D



注 記

- * 1) 造船所手配
- * 2) コネクタは工場にて取付済み。

NOTE

- *1. SHIPYARD SUPPLY
- *2. CONNECTOR PLUG FITTED AT FACTORY.

DRAWN	Jan. 25. '05 D. MILLS	TYPE	GD-1920C-BB
CHECKED	TAKAHASHI . T	名 称	カラービデオプロッタ
APPROVED	Y. Hatai		相互結線図
SCALE	MASS kg	NAME	COLOR VIDEO PLOTTER
DWG. No.	C4433-C01- A		INTERCONNECTION DIAGRAM