Customer	Qty.

ES-7A, ES-7D ACCESSORY PANEL ORDER FORM

This panel is designed for expanding AC OR DC circuit capacity on any Elite Series panel or it may be used as a stand-alone load center. Note: There is a modification fee for any configuration other than standard.

FEA	TU	IR	ES
TIME			LU

- AC or DC master breaker
- 16 branch circuit capacity, 12 installed standard
- Circuit "ON" indicator lights,
- LS-III label set included
- Panel size: 5 1/4"W x 15"H x 4"D
- Weight: 7 lbs.

OPTIONS

ES-7A: AC MASTER BREAKER *
(Double Pole)

___ 50 AMP (Standard; 115 VAC only) ___ 30 AMP (Optional; 115/230 VAC)

ES-7D: DC MASTER BREAKER

(Single Pole)

____ 100 AMP (Standard)

____ 60 AMP (Optional) ____ 50 AMP (Optional)

Both: BREAKER VALUES

Specify: 5, 10, 15, 20, 25, 30, 40, 50 amp on

illustration

Both: LABELS - FACTORY INSTALLED

See catalog for choices - Specify on illustration at right

* Note: If panel is wired for 230 VAC operation, master breaker must be 30 amp max.

Non-standard configuration modification fee: \$ 35.00 retail
Extra circuit breakers: Cost of breaker (see price list) plus \$ 1.00 each installed.

0.		-
	MASTER BREAKER	• 0)
	0	0
if U	0	0
		0
- 17		0
		0
		0
		0
		0
		0
		0
		,0
		0
		0
	0	0
×	0	0
15	0	0
(0		0